

MotionSwitch LED Z-Wave



Product code **4007841035402**

- Smart home via power socket. No cable. No batteries. No stress. The MotionSwitch LED Z-Wave is a motion detector, brightness sensor, button and orientation light in one. Above all, it is easy to integrate and operate: plug into the power socket, install via the Smart Friends app and control indoor lights, roller-shutter motors, sound systems, alarm systems etc. easily and conveniently.

The logo for neva lux, with 'neva' in black and 'lux' in yellow.

56 x 55 x 55 mm



MotionSwitch LED Z-Wave

Product code 4007841035402

Technical Data

IDENTIFICATION					
Version	Motion detectors	Tangential range	r = 20 m (628 m²)	Twilight setting teach	No
DIMENSIONS		Mounting height	0,20 – 1,10 m	HOUSING & MATERIAL	
Dimensions L x W x H	56 x 55 x 55 mm	Optimal mounting height	1,1 m	Protection class (IP)	IP20
ELECTRICAL		CONNECTIVITY		Ambient temperature	-10 – 35 °C
Mains connection	230 – 240 V / 50 Hz	Networking	Yes	Housing material	Plastic
Power	1,5 W	Networking via	Wireless	Mounting location	wall
Own consumption	0,3 W	LIGHTING TECHNOLOGY		Application location	Indoors
SENSOR TECHNOLOGY		Soft light start	No	Mounting type	Other
Max. mounting height	1,10 m	Constant light regulation	No	Material	Plastic
Sensor technology	passive infrared	SETTINGS		Application room	Indoors WC / washroom function room / ancillary room
With motion detector	Yes	Twilight switch	Yes	Colour	white
Detection angle	180 °	Twilight setting	2 – 2000 lx	RAL colour	9010
Opening angle	90 °	Time setting	5 s – 15 Min.	SCOPE OF DELIVERY & WARRANTY	
Sneak-under protection	Yes	Base light function	Yes	Manufacturer warranty	3 years
Segment-by-segment masking	No	Main light adjustable	No	Corner wall bracket included	No
Electronic scalability	No	Functions	Sensor channel\nOrientation light	CERTIFICATES & EPREL	
Mechanical scalability	No	Settings via	Z-Wave\nPotentiometers	Certificates	VDE
Radial range	r = 4 m (25 m²)	With remote control	No		

MotionSwitch LED Z-Wave

Product code 4007841035402

Illustrations

MOUNTING HEIGHT

0,20 – 1,10 m BEREICH	1,1 m OPTIMAL	1,10 m MAX
--------------------------	------------------	---------------

MotionSwitch LED Z-Wave

Product code **4007841035402**

Accessories

ORDERING INFORMATION

Art.-Nr. 4007841035402

Typ **MotionSwitch LED Z-Wave**

neva
lux

nevalux AG
Neugrütstrasse 2
8610 Uster
+41 44 508 78 78
info@nevalux.swiss