sensIQ eNet - black

MOTION DETECTOR

EAN 4007841020422

- 4x pyro system
- Suitable for mounting on ceilings
- UV-resistant plastic
- Wireless interconnection
- Including corner wall mount
- Smart Remote remote control optional
- Remote control RC9 included

144 x 113 x 172 mm



sensIQ eNet - black

MOTION DETECTOR

EAN 4007841020422

Technical Data

IDENTIFICATION

Variant	eNet - black
Version	Motion detectors
Type of accessory	Corner adapter

DIMENSIONS

Dimensions L × W × H	144 x 113 x 172 mm

ELECTRICAL

Mains connection	220 – 240 V , 50 / 60 Hz
Switching output 1 number of LED/fluorescent lamps	8 pcs.

SENSOR TECHNOLOGY

Sensor technology	passive infrared
Detection angle	300 °
Opening angle	90 °
Sneak-under protection	Yes
Segment-by-segment masking	Yes
Electronic scalability	No
Mechanical scalability	Yes
Range detail	Reach adjustable from 2 - 20 m in 3 directions (100° in each)
Radial range	r = 4 m (42 m²)
Tangential range	r = 20 m (1047 m²)
Switching zones	1360 switching zones
Mounting height	2,00 – 5,00 m
Optimal mounting height	2 m

CONNECTIVITY

Networking	Yes
With bus coupler	No
Control technology	On/Off-Leuchte

LIGHTING TECHNOLOGY

Constant light regulation	No

SETTINGS

Twilight setting	2 – 2000 lx
Time setting	5 sec – 15 min
Base light function	No
With remote control	Yes
Twilight setting teach	Yes

HOUSING & MATERIAL

Ambient temperature	-20 – 50 °C
Mounting location	ceiling corner wall
Application location	Indoors Outdoors
Mounting type	Surface wiring
Material	Plastic
Colour	black
RAL colour	9005

SCOPE OF DELIVERY & WARRANTY

Manufacturer warranty	5 years

CERTIFICATES & EPREL

Certificates	VDE

OTHER

Application, location, room	multi-storey car park, underground car park

sensIQ eNet - black

MOTION DETECTOR

EAN 4007841020422

Illustrations

MOUNTING HEIGHT

2,00 – 5,00 m BEREICH	2 m OPTIMAL

sensIQ eNet - black

MOTION DETECTOR

EAN 4007841020422

Accessories

	ARTICLE NUMBER	DESCRIPTION	CATEGORY
	4007841609115	**MPF1 Potentialfreimodul SensIQ**	Accessory
	4007841009151	**Smart Remote**	Accessory
	4007841032821	**eNet Funk Handsender 2-fach**	Accessory
	4007841032838	**eNet Schaltaktor**	Accessory

ORDERING INFORMATION

Art.-Nr.	4007841020422
EAN	4007841020422
Typ	**sensIQ eNet - black**

nevalux AG
Neugrütstrasse 2
8610 Uster
+41 44 508 78 78
info@nevalux.swiss